

|                   |                                |
|-------------------|--------------------------------|
| PRODUCT MATERIAL  | Die-cast aluminium + Alabaster |
| ADAPTER           | 48V track adapter              |
| LIGHT SOURCE      | Bridgelux V6HD                 |
| MODULE LIFETIME   | Approx. 50.000 hours           |
| DRIVER            | Including DALI driver          |
| COLORS            | ● 5 = RAL 9005 black           |
| ADJUSTABLE        | No                             |
| SIZE              | Ø120mm                         |
| OPTIONS           |                                |
| WIRELESS DIMMABLE | Zigbee or Casambi              |

INFORMATION


This fixture is supplied as standard with 3 meters of cable. Should you require a shorter length, please indicate your preference, and we will customize the cable to your desired length. It is not possible to shorten the cable yourself.

**The Unique Beauty of Alabaster in Lighting Design**  
The natural translucency of alabaster allows for a soft, diffuse distribution of light, creating a warm and inviting atmosphere. Each piece of natural alabaster stone is uniquely veined, ensuring that no two examples are ever the same.

**What Colors Does Alabaster Come In?**  
Alabaster can range from white and yellow to brown, with some varieties leaning towards pink or gray tones.

**Characteristics of Gypsum Alabaster (or Selenite)**  
Gypsum alabaster is a translucent type of stone composed of partially crystallized gypsum. It is typically found in nodular forms in regions such as Italy, Spain, and Egypt. The outer surface of alabaster nodules often features irregularities, with clay residues and earthy inclusions embedded within the stone. These natural impurities are a hallmark of alabaster, contributing to its distinctive charm.

**Not to Be Confused with Marble**  
Alabaster is a semi-crystalline form of gypsum, differing from marble, which is a type of limestone it often resembles. Unlike many other stones extracted from quarries, alabaster is discovered in nodules beneath the ground. Depending on its origin, alabaster can display a wide variety of colors, adding to its versatility and appeal in design. This unique combination of translucency, texture, and color makes alabaster a timeless choice for creating elegant and atmospheric lighting solutions.



| ARTICLE NUMBER | LAMP TYPE | BRAND     | LUMINOUS FLUX | OUTPUT POWER | MODULE EFFICIENCY | COLOR TEMPERATURE | CRI | TC LIFETIME | mA    |
|----------------|-----------|-----------|---------------|--------------|-------------------|-------------------|-----|-------------|-------|
| 5731.275.08.5  | V6HD      | Bridgelux | 239lm         | 6W           | 40lm/W            | 2700K             | >90 | 50.000 Hrs  | 150mA |
| 5731.305.08.5  | V6HD      | Bridgelux | 260lm         | 6W           | 43lm/W            | 3000K             | >90 | 50.000 Hrs  | 150mA |